

Kangaroo

WIRING PLAN "KANGAROO"

SOLDER FACE

-5V 28
+12V 27
+5V 26
+5V 25
TV. RED 24
TV. SYNC 23
GROUND 22
21
20
19
18
17
16
15
14
13
12
11 2P-PUNCH
10 2P-JUMP/UP
9 2P-RIGHT
8
7 1P-PUNCH
6 1P-JUMP/UP
5 1P-RIGHT
4 TABLE TYPE
3
2 2P-SELECT
1 GROUND

PARTS FACE

-5 V
+12V
+5V
+5V
TV. BLUE
TV. GREEN
GROUND

SOUND CUT

2P-DOWN
2P-LEFT

1P-DOWN
1P-LEFT

COIN
1P-SELECT
GROUND

PARTS FACE

28 1

EXPLANATION OF "DIP SWITCH"

DIP SW. NO.1 -"ON" —5PCS. OF KANGAROO
NO.2 -"ON" —SELL COIN TO SECOND LINE
NO.3 -"ON" —2 COIN 1 CREDIT
NO.4 -"ON" —1 COIN 2 CREDIT

FOR TABLE TYPE

FACTORY'S SPECIFICATIONS FOR "UP-RIGHT". SO IF YOU WANT TO
CHANGE TO TABLE, PLS CONNECT NO4 (SOLDER FACE) ON PCB TO GROUND

Känguruli

IM

Bestückungsliste

Lötliste

1 P START	1	2 P START
Münze EIN	2	
GND	3	
GND	4	1 P RECHTS
1 P Links	5	1 P AUF
1 P AB	6	1 P TASTER 1:
	7	
	8	
	9	
	10	
	11	
	12	
	13	
	14	
	15	Lautsprecher ⊕
GND	16	Lautsprecher ⊖
GND	17	GND
GND	18	GND
GND	19	GND
+ 5V	20	+ 5V
+ 5V	21	+ 5V
+ 12V	22	+ 12V
<hr/>		
Kleiner Platinenspeicher 1 A - TV ROT	23	
2 A - TV GRÜN	24	
3 A - TV BLAU	25	
4 A - TV Synchron	26	
↓ GND	27	
GND	28	
10A GND		
+ 5V		
+ 12V		
+ 5V		

Kangevoo

UNISKO VIDEO SPIELE FFM

NACHBAU!PARTSIDESOLDERSIDE

1 1 Player Start

1 2 Player Start

2 Coin 1

2 Coin 2

3 GND

3 Table - GND

4 GND

4 1 Player Right

5 1 Player Left

5 1 Player Up

6 1 Player Down

6 1 Player Punch

7

7

8 Test

8 2 Player Right

9 2 Player Left

9 2 Player Up

10 2 Player Down

10 2 Player Punch

11

11

12

12 Sync

13 Blue

13 Green

14 Red

14 GND

15 Coin Counter 1

15 Coin Counter 2

16 Speaker

16 Speaker

17 -5V

17 -5V

18 +12V

18 +12V

19 +5V

19 +5V

20 +5V

20 +5V

21 GND

21 GND

22 GND

22 GND

IC 46 Pin 14

Name	Klasse	Datum	Blatt
Königshoruh			
		Übung:	
1 Masse	A Masse		
2 Masse	B Masse		
3 SVDC	C SVDC		
4 SVDC	D SVDC		
5 Lautspr.	E		
6 rechts PL2	F		
7 schlagen PL2	H		
8 links PL2	J		
9 links PL1	K rechts PL1		
10 ducken PL1	L springen PL1		
11 ducken PL2	M		
12 springen PL2	N schlagen PL1		
13 1PL Start	P		
14 Credit 6x	R Credit 1x		
15 2PL Start	S		
16 rot	T Grün		
17 blau	U Synchro		
18 Lautspr.	V -SVDC		
19	V 12VDC		
20	X Table		
21	Y Masse		
22	Z		

